



## Current Equipment Type

**TYPE UY85**  
AC/DC HALF-WAVE  
RECTIFIER



The BRIMAR Type UY85 is a half-wave rectifier for use in A.C./D.C. receivers where a 0.1 amp. series heater chain is employed.

Heater Current	...	...	...	...	...	...	0.1 amp.
Heater Voltage	...	...	...	...	...	...	38 volts

## RATINGS

Maximum P.I.V.	...	...	...	...	...	...	700 volts
Maximum Output Current	...	...	...	...	...	...	110 mA
Maximum Peak Current	...	...	...	...	...	...	660 mA
Maximum Heater Cathode Voltage (cathode positive)	...	...	...	...	...	...	550 volts

## OPERATING CHARACTERISTICS

Input Voltage...	...	...	...	...	...	...	250 volts
Output Current	...	...	...	...	...	...	110 mA
Output Voltage	...	...	...	...	...	...	245 volts
Reservoir Capacitor	...	...	...	...	...	...	100 $\mu$ F
Limiting Resistor	...	...	...	...	...	...	100 ohms

