


### TIME BASE TRIODE PENTODE



#### GENERAL

This triode pentode is for use in television receivers with the triode as a frame blocking oscillator and the pentode as a frame output valve.

Heater Current	$I_h$	0.3	A
Heater Voltage	$V_h$	12.6	V

#### RATINGS

	Triode	Pentode	
Maximum Anode Dissipation	Pa(max)	3.5	5.4
Maximum Screen Grid Dissipation Speech and Music	Pg <sub>2</sub> (max)	—	1.2
Maximum Anode Supply Voltage	V <sub>a(b)</sub> max	550	V
Maximum Anode Voltage	V <sub>a</sub> (max)	250	V
Maximum Peak Positive Anode Voltage	V <sub>a(pk)</sub> max	—	kV
Maximum Screen Grid Supply Voltage	V <sub>g2(b)</sub> max	—	V
Maximum Screen Grid Voltage	V <sub>g2</sub> (max)	—	V
Maximum Heater to Cathode Voltage Heater Positive	V <sub>h-k</sub> (max)	250	V
Maximum Cathode Current	I <sub>k</sub> (max)	100	V
Maximum Control Grid to Cathode Resistance Self Bias	R <sub>g1-k</sub> (max)	15	mA
Fixed Bias	—	45	mA
Grid Current Bias	1.0	500	kΩ
	22	—	MΩ

#### INTER-ELECTRODE CAPACITANCES

	Triode	Pentode	
Input	C <sub>in</sub>	2.3	pF
Output	C <sub>out</sub>	0.32	pF
Anode to Control Grid	C <sub>a-g<sub>1</sub></sub>	1.6	pF
Control Grid to Heater	C <sub>g<sub>1</sub>-h</sub>	—	pF

#### OPERATING CHARACTERISTICS

	Triode	Pentode	
Anode Voltage	V <sub>a</sub>	250	V
Screen Grid Voltage	V <sub>g<sub>2</sub></sub>	—	V
Control Grid Voltage	V <sub>g<sub>1</sub></sub>	—8.5	V
Anode Current	I <sub>a</sub>	10.5	mA
Screen Grid Current	I <sub>g<sub>2</sub></sub>	—	mA
Mutual Conductance	gm	2.2	mA/V
Valve Anode Resistance ( $\delta V_a / \delta I_a$ )	r <sub>a</sub>	7.7	kΩ
Amplification Factor	$\mu$	17	—
Inner Amplification Factor	$\mu_{g1-g2}$	—	10